

Make a call	
Handset	Lift Handset + Internal Number Lift Handset + 9 + External Number
Speaker	[Speaker] + Internal Number or [Speaker] + 9 + External Number
Directory	[Phone Bk] + Personal Addr Book +
Call Lists	[PBX] + List of calls +
Redial	REDIAL

Make a second Call while on a call	[OPTIONS] + Internal Number or [HOLD] + 9 + External Number
------------------------------------	---

Answer a call	
Handset	Lift Handset
Speaker	[Answer] or [Speaker]
Headset	[Answer]
answer a second call	[Answer] or [Options]

Handle a Call	
Hold/Retrieve	[OPTIONS] + Hold
Transfer	[OPTIONS] + Transfer

Forward	
Clear Forward	
Forward on busy	[Menu] + Call Features + Call Forward + Forward on busy
Forward no Answer	[Menu] + Call Features + Call Forward + Forward no Answer

--	--

Voicemail	
Listen to voicemails	[Menu] + Voicemail
Change Greeting	[Menu] + Voicemail + Setup Voice Mail + Intro Message + Record
Remote Access	Dial # during voicemail greeting + PIN



Magnet Voice


Yealink W52P phone








Quick Reference Guide

Magnet Voice

Yealink W52P phone



Item	Description
① Earpiece	Outputs audio during the earpiece call.
② LCD Screen	Shows call information, handset status icons, prompt messages and so on.
③ Soft Keys	Label automatically to identify their context-sensitive features.
④ Speakerphone Key	Switches between the earpiece and speakerphone modes. Answers an incoming call.
⑤ Headset Connector	Connects a headset.
⑥ Off-hook Key	Answers an incoming call. Enters the redial call list. Places a call.
⑦ Key pad	Provides digits, letters and special characters in context-sensitive applications.
⑧ Star Key	Enter s the star symbol . Switches the silent mode on or off.
⑨ Redirect Key	Transfers a call to another party .

Item	Description	
⑩ Microphone	Picks up audio during earpiece and hands-free calls.	
⑪ Mute Key	Toggles Mute feature on or off.	
⑫ Pound Key	Enters the pound symbol . Locks or unlocks the handset keypad. Switches the input method .	
⑬ On-hook Key /Power key	Long presses in the menu screen to return to the idle screen . Long presses to turn the handset on or off when the handset is idle. Cancels actions or ends a call. Rejects an incoming call.	
⑭ Message Key	Indicates a new receiving voice mail or a missed call. Accesses the voicemail or the missed call list.	
⑮	 	Move the cursor. Act as shortcuts. Scroll through the displaying information.
	 	M ove the cursor. Act as shortcuts. Adjust the ringer volume. Switch the values.
		Confirms actions or enters the main menu.

Connecting to Magnet Voice

Connect the LAN port on the underside of the phone to the LAN switch/hub with an Ethernet cable. Plug the DC power Supply into the phone and into the mains. The phone also supports power over the Ethernet Cable. The phone will power up and automatically register with the Magnet voice System and display the time, date and user number.

Please consult the Magnet Voice full installation manual.
www.magnet.ie/business/support/userguides

Login to your personal Magnet Voice Phone portal

you can easily manage your Magnet Voice Phone settings, personal phonebook, call diversions and voicemails by logging into Magnet Voice Online from your browser.

Contact the Magnet Voice Online system administrator to receive your Username and PIN